

INFORMATION TRANSMISSION UNDER MARKOVIAN NOISE

SATVIK SINGH AND NILANJANA DATTA

ABSTRACT. We consider an open quantum system undergoing Markovian dynamics, the latter being modelled by a discrete-time quantum Markov semigroup $\{\Phi^n\}_{n \in \mathbb{N}}$, resulting from the action of sequential uses of a quantum channel Φ , with $n \in \mathbb{N}$ being the discrete time parameter. We find upper and lower bounds on the one-shot ε -error information transmission capacities of Φ^n for a finite time $n \in \mathbb{N}$ and $\varepsilon \in [0, 1)$ in terms of the structure of the peripheral space of the channel Φ . We consider transmission of (i) classical information (both in the unassisted and entanglement-assisted settings); (ii) quantum information and (iii) private classical information.

1. INTRODUCTION

The time evolution of an *open quantum system*, i.e. one which interacts with its surroundings, can be considered to be Markovian when the interactions are assumed to be weak. In this scenario, the dynamics of the system can be modelled by a quantum Markov semigroup (QMS). More precisely, let A denote an open quantum system with the associated finite-dimensional Hilbert space \mathcal{H}_A and the algebra $\mathcal{L}(\mathcal{H}_A)$ of linear operators acting on \mathcal{H}_A . Then, in the discrete-time case, the QMS is given by $\{\Phi^n\}_{n \in \mathbb{N}}$, where $\Phi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_A)$ is a quantum channel (i.e. a linear completely positive trace-preserving map), $\Phi^n = \Phi \circ \Phi \cdots \circ \Phi$ denotes the n -fold composition of Φ with itself, and $n \in \mathbb{N}$ plays the role of the discrete time parameter. The nomenclature is justified by the fact that $\{\Phi^n\}_{n \in \mathbb{N}}$ satisfies the semigroup property: $\Phi^{n+m} = \Phi^n \circ \Phi^m$ for $n, m \in \mathbb{N}$.

In this paper, we analyze the information-transmission capacities of a discrete-time QMS $\{\Phi^n\}_{n \in \mathbb{N}}$, for which we use the acronym dQMS. Note that since n sequential uses of Φ corresponds to a *single use* of Φ^n , we are interested in the *one-shot* information-transmission capacities of Φ^n for $n \in \mathbb{N}$. Put differently, we consider the task of storing information in an open quantum system A in such a way that the information can be reliably recovered (with some error $\varepsilon \in [0, 1)$) after the system is left to evolve according to the dQMS $\{\Phi^n\}_{n \in \mathbb{N}}$ for some finite time $n \in \mathbb{N}$. This problem was recently studied in [SRD24] in the asymptotic time limit $n \rightarrow \infty$ for error $\varepsilon = 0$ (see also [GFY16, Section V]), and in [FRT24] in the asymptotic time limit $n \rightarrow \infty$ for error $\varepsilon \in [0, 1)$.

As is well-known, a quantum channel has several kinds of information-transmission capacities. These depend, for example, on the nature of the information being transmitted (classical or quantum), whether there are any auxiliary resources that the sender and receiver might employ in the information-transmission task (e.g. pre-shared entanglement), and whether the information to be transmitted is private, i.e. required to be inaccessible to an eavesdropper. In view of these considerations, we study the classical, quantum, entanglement-assisted classical, and private classical capacities in this paper.

Note that in the familiar *asymptotic, memoryless setting* of quantum Shannon theory, one evaluates capacities of a quantum channel, Φ , in the *parallel setting*. This corresponds to evaluating the optimal rate of information transmission through $\Phi^{\otimes n}$ in the limit $n \rightarrow \infty$, under the requirement that the error incurred in the transmission vanishes in this limit. In contrast, here we consider information transmission through Φ in the *sequential setting*, that is, through n sequential uses of Φ . In addition, we focus on the more realistic scenario in which we consider using Φ a finite number of times in succession (i.e. $n < \infty$) and allow a non-zero probability of error (say, $\varepsilon \in [0, 1)$) in transmitting the information through Φ^n .

Layout of the paper: In Section 2 we introduce the relevant mathematical notation and definitions, as well as the information-processing tasks (or protocols) considered in this paper. Our main result is stated in Theorem 3.1. The theorem provides upper and lower bounds on the one-shot ε -error capacities of Φ^n for finite $n \in \mathbb{N}$ in terms of the structure of the peripheral space of Φ . Some technical lemmas which are used in the proof of Theorem 3.1 are stated and proved in Appendix A. The corresponding upper and lower bounds on the one-shot ε -error capacities of Φ^n in the asymptotic time limit ($n \rightarrow \infty$) are stated in Corollary 3.3.

2. PRELIMINARIES

We denote quantum systems by capital letters A, B, C and the associated (finite-dimensional) Hilbert spaces by $\mathcal{H}_A, \mathcal{H}_B$ and \mathcal{H}_C with dimensions d_A, d_B and d_C , respectively. For a joint system AB , the associated Hilbert space is $\mathcal{H}_A \otimes \mathcal{H}_B$. The space of linear operators acting on \mathcal{H}_A is denoted by $\mathcal{L}(\mathcal{H}_A)$ and the convex set of quantum states or density operators (these are positive semi-definite operators in $\mathcal{L}(\mathcal{H}_A)$ with unit trace) is denoted by $\mathcal{D}(\mathcal{H}_A)$. For a unit vector $|\psi\rangle \in \mathcal{H}_A$, the pure state $|\psi\rangle\langle\psi| \in \mathcal{D}(\mathcal{H}_A)$ is denoted by ψ . A quantum channel $\Phi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_B)$ is a linear, completely positive, and trace preserving map. By Stinespring's dilation theorem, for a quantum channel $\Phi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_B)$, there exists an isometry $V : \mathcal{H}_A \rightarrow \mathcal{H}_B \otimes \mathcal{H}_E$ (called the Stinespring isometry) such that for all $X \in \mathcal{L}(\mathcal{H}_A)$, $\Phi(X) = \text{Tr}_E(VXV^\dagger)$, where Tr_E denotes the partial trace operation over the E subsystem. The corresponding complementary channel $\Phi^c : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_E)$ is then defined as $\Phi^c(X) = \text{Tr}_B(VXV^\dagger)$. The adjoint Φ^* of a quantum channel $\Phi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_B)$ is defined through the following relation: $\text{Tr}(Y\Phi(X)) = \text{Tr}(\Phi^*(Y)X)$ for any $X \in \mathcal{L}(\mathcal{H}_A)$ and $Y \in \mathcal{L}(\mathcal{H}_B)$.

Remark 2.1. *To make the systems on which an operator or a channel acts more explicit, we sometimes denote operators $X \in \mathcal{L}(\mathcal{H}_A)$ and linear maps $\Phi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_B)$ by X_A and $\Phi_{A \rightarrow B}$, respectively.*

For a bipartite operator X_{RA} and a linear map $\Phi_{A \rightarrow B}$, we use the shorthand $\Phi_{A \rightarrow B}(X_{RA})$ to denote $(\text{id}_R \otimes \Phi_{A \rightarrow B})(X_{RA})$, where id_R is the identity map on $\mathcal{L}(\mathcal{H}_R)$. Similarly, X_R and X_A denote the reduced operators on R and A , respectively, i.e. $X_R := \text{Tr}_A X_{RA}$ and $X_A := \text{Tr}_R X_{RA}$.

The trace norm of a linear operator $X \in \mathcal{L}(\mathcal{H}_A)$ is defined as $\|X\|_1 := \text{Tr} \sqrt{X^\dagger X}$. The diamond norm of a linear map $\Phi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_B)$ is defined as

$$\|\Phi\|_\diamond := \sup_{\|X\|_1 \leq 1} \|\Phi_{A \rightarrow B}(X_{RA})\|_1, \quad (1)$$

where the supremum is over all $X \in \mathcal{L}(\mathcal{H}_R \otimes \mathcal{H}_A)$ with $d_R = d_A$ and $\|X\|_1 \leq 1$. We denote the operator norm of $X \in \mathcal{L}(\mathcal{H}_A)$ by $\|X\|_\infty$.

The max-relative entropy between two positive semi-definite operators $\rho, \sigma \in \mathcal{L}(\mathcal{H}_A)$ is defined as [Dat09b]:

$$D_{\max}(\rho\|\sigma) := \log \inf\{\lambda : \rho \leq \lambda\sigma\}, \quad (2)$$

where the infimum over an empty set is assumed to be $+\infty$. When $\text{supp}\rho \subseteq \text{supp}\sigma$,

$$D_{\max}(\rho\|\sigma) = \log \left\| \sigma^{-1/2} \rho \sigma^{-1/2} \right\|_\infty. \quad (3)$$

The max-relative entropy is quasi-convex: for positive semi-definite operators $\{\rho_i\}_i, \{\sigma_i\}_i \subset \mathcal{L}(\mathcal{H}_A)$:

$$D_{\max} \left(\sum_i \rho_i \left\| \sum_i \sigma_i \right. \right) \leq \max_i D_{\max}(\rho_i\|\sigma_i). \quad (4)$$

Moreover, if for each i , ρ_i and σ_i are supported on a subspace $\mathcal{H}_i \subseteq \mathcal{H}_A$ such that for $i \neq j$, $\mathcal{H}_i \perp \mathcal{H}_j$, the inequality above becomes an equality.

The ε -hypothesis testing relative entropy between a state $\rho \in \mathcal{D}(\mathcal{H}_A)$ and a positive semi-definite operator $\sigma \in \mathcal{L}(\mathcal{H}_A)$ with $\varepsilon \in [0, 1]$ is defined as follows [WR12]:

$$D_H^\varepsilon(\rho \parallel \sigma) := -\log \beta_H^\varepsilon(\rho \parallel \sigma), \quad (5)$$

where

$$\beta_H^\varepsilon(\rho \parallel \sigma) := \inf_{0 \leq \Lambda \leq \mathbb{1}} \{\text{Tr } \Lambda \sigma : \text{Tr } \Lambda \rho \geq 1 - \varepsilon\}. \quad (6)$$

The ε -hypothesis testing relative entropy of entanglement of a state ρ_{AB} is defined as

$$E_H^\varepsilon(A : B)_\rho := \inf_{\sigma_{AB} \in \text{SEP}(A:B)} D_H^\varepsilon(\rho_{AB} \parallel \sigma_{AB}), \quad (7)$$

where the infimum is over the set $\text{SEP}(A : B)$ of all separable states in $\mathcal{D}(\mathcal{H}_A \otimes \mathcal{H}_B)$.

The ε -hypothesis testing relative entropy of entanglement of a channel $\Phi_{A \rightarrow B}$ is defined as

$$E_H^\varepsilon(\Phi) := \sup_{\rho_{RA}} E_H^\varepsilon(R : B)_\omega = \sup_{\rho_{RA}} \inf_{\sigma_{RB} \in \text{SEP}(R:B)} D_H^\varepsilon(\Phi_{A \rightarrow B}(\rho_{RA}) \parallel \sigma_{RB}), \quad (8)$$

where the supremum is over all states ρ_{RA} and $\omega_{RB} = \Phi_{A \rightarrow B}(\rho_{RA})$. It can be shown that the supremum here can be restricted to pure states ψ_{RA} with $d_R = d_A$.

2.1. Classical communication. An $(\mathcal{M}, \varepsilon)$ classical communication protocol with $\mathcal{M} \in \mathbb{N}$ and $\varepsilon \in [0, 1)$ for a channel $\Phi_{A \rightarrow B}$ consists of the following:

- Encoding states ρ_A^m that Alice uses to encode a message $m \in [\mathcal{M}] := \{1, 2, \dots, \mathcal{M}\}$.
- Decoding POVM $\{\Lambda_B^m\}_{m \in [\mathcal{M}]}$ that Bob uses to decode the message,

such that for each message m ,

$$\text{Tr}[\Lambda_B^m(\Phi_{A \rightarrow B}(\rho_A^m))] \geq 1 - \varepsilon. \quad (9)$$

The one-shot ε -error classical capacity of Φ is defined as

$$C_\varepsilon(\Phi) := \sup\{\log \mathcal{M} : \exists(\mathcal{M}, \bar{\varepsilon}) \text{ classical communication protocol for } \Phi \text{ with } \bar{\varepsilon} \leq \varepsilon\}. \quad (10)$$

Remark 2.2. *In the literature, one-shot communication capacities are usually denoted as $C_\varepsilon^{(1)}(\Phi)$. However, since all the capacities considered in this paper are one-shot, we omit the superscript (1) for notational simplicity.*

2.2. Private classical communication. An $(\mathcal{M}, \varepsilon)$ private classical communication protocol through a channel $\Phi_{A \rightarrow B}$ consists of the following:

- Encoding states ρ_A^m that Alice uses to encode a message $m \in [\mathcal{M}]$.
- Decoding POVM $\{\Lambda_B^m\}_{m \in [\mathcal{M}]}$ with an associated channel $\mathcal{D}_{B \rightarrow M'}$ defined as $\mathcal{D}(\cdot) = \sum_m \text{Tr}(\Lambda_B^m(\cdot)) |m\rangle\langle m|_{M'}$ that Bob uses to decode the message,

such that for each message m ,

$$F(|m\rangle\langle m|_{M'} \otimes \sigma_E, \mathcal{D}_{B \rightarrow M'} \circ \mathcal{V}_{A \rightarrow BE}(\rho_A^m)) \geq 1 - \varepsilon, \quad (11)$$

where σ_E is some fixed state independent of m and $\mathcal{V}_{A \rightarrow BE}(\cdot) = V(\cdot)V^\dagger$, where $V : \mathcal{H}_A \rightarrow \mathcal{H}_B \otimes \mathcal{H}_E$ is a Stinespring isometry of $\Phi_{A \rightarrow B}$. By using the data processing inequality for the fidelity function, it is easy to show that the above condition implies:

$$\forall m : \quad \text{Tr}[\Lambda_B^m(\Phi_{A \rightarrow B}(\rho_A^m))] \geq 1 - \varepsilon, \quad (12)$$

$$F(\sigma_E, \Phi_{A \rightarrow E}^c(\rho_A^m)) \geq 1 - \varepsilon, \quad (13)$$

where $\Phi_{A \rightarrow E}^c$ denotes a quantum channel which is complementary to $\Phi_{A \rightarrow B}$.

The one-shot ε -error private classical capacity of Φ is defined as

$$C_\varepsilon^P(\Phi) := \sup\{\log \mathcal{M} : \exists(\mathcal{M}, \bar{\varepsilon}) \text{ private classical communication protocol for } \Phi \text{ with } \bar{\varepsilon} \leq \varepsilon\}. \quad (14)$$

2.3. Entanglement-assisted classical communication. An $(\mathcal{M}, \varepsilon)$ entanglement-assisted classical communication protocol through a channel $\Phi_{A \rightarrow B}$ consists of the following:

- An entangled state $\psi_{A'B'}$ shared between Alice and Bob,
- Encoding channels $\mathcal{E}_{A' \rightarrow A}^m$ that Alice uses to encode a message $m \in [\mathcal{M}]$,
- Decoding POVM $\{\Lambda_{BB'}^m\}_{m \in [\mathcal{M}]}$ that Bob uses to decode the message,

such that for each message m ,

$$\mathrm{Tr}[\Lambda_{BB'}^m(\Phi_{A \rightarrow B} \circ \mathcal{E}_{A' \rightarrow A}^m(\psi_{A'B'}))] \geq 1 - \varepsilon. \quad (15)$$

The one-shot ε -error entanglement-assisted classical capacity of Φ is defined as

$$C_\varepsilon^{\mathrm{ea}}(\Phi) := \sup\{\log \mathcal{M} : \exists(\mathcal{M}, \bar{\varepsilon}) \text{ entanglement-assisted} \quad (16)$$

$$\text{classical communication protocol for } \Phi \text{ with } \bar{\varepsilon} \leq \varepsilon\}. \quad (17)$$

2.4. Quantum communication. A (d, ε) quantum communication protocol $(\mathcal{E}_{A' \rightarrow A}, \mathcal{D}_{B \rightarrow B'})$ for a channel $\Phi_{A \rightarrow B}$ consists of the following ($d = d_{A'} = d_{B'}$):

- An encoding channel $\mathcal{E}_{A' \rightarrow A}$ that Alice uses to encode quantum information,
- A decoding channel $\mathcal{D}_{B \rightarrow B'}$ that Bob uses to decode the information,

such that for every pure state $\psi_{RA'}$

$$\langle \psi_{RB'} | \mathcal{D}_{B \rightarrow B'} \circ \Phi_{A \rightarrow B} \circ \mathcal{E}_{A' \rightarrow A}(\psi_{RA'}) | \psi_{RB'} \rangle \geq 1 - \varepsilon. \quad (18)$$

The one-shot ε -error quantum capacity of Φ is defined as

$$Q_\varepsilon(\Phi) := \sup\{\log d : \exists(d, \bar{\varepsilon}) \text{ quantum communication protocol for } \Phi \text{ with } \bar{\varepsilon} \leq \varepsilon\}. \quad (19)$$

2.5. Spectral properties of quantum channels. Let $\Phi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_A)$ be a quantum channel. Then, Φ admits a Jordan decomposition [Wol12, Chapter 6]

$$\Phi = \sum_i \lambda_i \mathcal{P}_i + \mathcal{N}_i \quad \text{with} \quad \mathcal{N}_i \mathcal{P}_i = \mathcal{P}_i \mathcal{N}_i = \mathcal{N}_i \quad \text{and} \quad \mathcal{P}_i \mathcal{P}_j = \delta_{ij} \mathcal{P}_i, \quad (20)$$

where the sum runs over the distinct eigenvalues λ_i of Φ , \mathcal{P}_i are projectors (i.e. $\mathcal{P}_i^2 = \mathcal{P}_i$) whose rank equals the algebraic multiplicity of λ_i , and \mathcal{N}_i denote the corresponding nilpotent operators.

All the eigenvalues λ of Φ satisfy $|\lambda| \leq 1$, and $\lambda = 1$ is always an eigenvalue. Moreover, all eigenvalues λ with $|\lambda| = 1$ have equal algebraic and geometric multiplicities, so that $\mathcal{N}_i = 0$ for all such eigenvalues. As $n \rightarrow \infty$, we expect the image of

$$\Phi^n := \underbrace{\Phi \circ \Phi \circ \dots \circ \Phi}_{n \text{ times}} \quad (21)$$

to converge to the peripheral space $\chi(\Phi) := \mathrm{span}\{X \in \mathcal{L}(\mathcal{H}_A) : \Phi(X) = \lambda X, |\lambda| = 1\}$. We define the asymptotic part of Φ and the projector onto the peripheral space, respectively, as follows:

$$\Phi_\infty := \sum_{i: |\lambda_i|=1} \lambda_i \mathcal{P}_i \quad \text{and} \quad \mathcal{P} = \sum_{i: |\lambda_i|=1} \mathcal{P}_i. \quad (22)$$

Clearly, $\Phi_\infty = \Phi_\infty \circ \mathcal{P} = \mathcal{P} \circ \Phi_\infty$. Notably, both $\Phi_\infty : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_A)$ and $\mathcal{P} : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_A)$ arise as limit points of the set $\{\Phi^n\}_{n \in \mathbb{N}}$ [SRW14, Lemma 3.1]. Since the set of quantum channels acting on \mathcal{H}_A is closed, both Φ_∞ and \mathcal{P} are quantum channels themselves. As n increases, $\|\Phi^n - \Phi_\infty^n\|_\diamond$ approaches zero. More precisely, the convergence behavior is like

$$\|\Phi^n - \Phi_\infty^n\|_\diamond \leq \kappa \mu^n, \quad (23)$$

where $\mu < 1$ is the spectral radius of $\Phi - \Phi_\infty$ (i.e. μ is the magnitude of the largest eigenvalue of $\Phi - \Phi_\infty$) and κ depends on the spectrum of Φ , on n , and on the dimension d_A of \mathcal{H}_A [SRW14]. The dependence of κ on n is sub-exponential, which captures the fact that for large n , the convergence

is governed by an exponential decay as μ^n . It is known that there exists a decomposition $\mathcal{H}_A = \mathcal{H}_0 \oplus \bigoplus_{k=1}^K \mathcal{H}_{k,1} \otimes \mathcal{H}_{k,2}$ and positive definite states $\delta_k \in \mathcal{D}(\mathcal{H}_{k,2})$ such that [Wol12, Chapter 6]:

$$\chi(\Phi) = 0 \oplus \bigoplus_{k=1}^K (\mathcal{L}(\mathcal{H}_{k,1}) \otimes \delta_k). \quad (24)$$

Moreover, there exist unitaries $U_k \in \mathcal{L}(\mathcal{H}_{k,1})$ and a permutation π which permutes within subsets of $\{1, 2, \dots, K\}$ for which the corresponding $\mathcal{H}_{k,1}$'s have the same dimension, such that for any

$$X = 0 \oplus \bigoplus_{k=1}^K x_k \otimes \delta_k, \quad \text{we have} \quad \Phi(X) = 0 \oplus \bigoplus_{k=1}^K U_k^\dagger x_{\pi(k)} U_k \otimes \delta_k. \quad (25)$$

Given a channel $\Phi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_A)$, the structure of its peripheral space $\chi(\Phi)$, i.e., the block dimensions $d_k = \dim \mathcal{H}_{k,1}$ and the states δ_k in Eq. (24), can be efficiently computed (see [FRT24, Section 4] and references therein).

3. MAIN RESULT

We can now state and prove our main result.

Theorem 3.1. *Let $\Phi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_A)$ be a quantum channel and $(\Phi^n)_{n \in \mathbb{N}}$ be the associated dQMS. Then, for all $\varepsilon \in [0, 1)$ and $n \in \mathbb{N}$, the one-shot ε -error capacities satisfy:*

$$Q_\varepsilon(\Phi^n) \geq \log \left(\max_k d_k \right), \quad (26)$$

$$C_\varepsilon^p(\Phi^n) \geq \log \left(\max_k d_k \right), \quad (27)$$

$$C_\varepsilon(\Phi^n) \geq \log \left(\sum_k d_k \right), \quad (28)$$

$$C_\varepsilon^{\text{ea}}(\Phi^n) \geq \log \left(\sum_k d_k^2 \right). \quad (29)$$

Moreover, for all $\varepsilon \in [0, 1)$ and n large enough, the one-shot ε -error capacities satisfy:

$$Q_\varepsilon(\Phi^n) \leq \log \left(\max_k d_k \right) + \log \left(\frac{1}{1 - \varepsilon - \kappa \mu^n} \right), \quad (30)$$

$$C_\varepsilon^p(\Phi^n) \leq \log \left(\max_k d_k \right) + \log \left(\frac{1}{1 - \varepsilon - \kappa \mu^n} \right) \quad (31)$$

$$C_\varepsilon(\Phi^n) \leq \log \left(\sum_k d_k \right) + \log \left(\frac{1}{1 - \varepsilon - \kappa \mu^n} \right), \quad (32)$$

$$C_\varepsilon^{\text{ea}}(\Phi^n) \leq \log \left(\sum_k d_k^2 \right) + \log \left(\frac{1}{1 - \varepsilon - \kappa \mu^n} \right). \quad (33)$$

Here, $d_k = \dim \mathcal{H}_{k,1}$ for $k \in \{1, 2, \dots, K\}$ are the block dimensions in the decomposition of $\chi(\Phi)$ (see Eq. (24)), μ, κ are constants that govern the convergence $\|\Phi^n - \Phi_\infty^n\|_\diamond \leq \kappa \mu^n \rightarrow 0$ as $n \rightarrow \infty$ (see Eq. (23)), and n is large enough so that $\varepsilon + \kappa \mu^n < 1$.

Remark 3.2. *The achievability bounds in Eqs. (26)-(29) are obtained by constructing communication protocols that work with $\varepsilon = 0$ error. It is unclear whether these bounds can be improved by explicitly taking ε into account. In this regard, we note that the achievability bounds in [FRT24] on the quantum and classical capacities do take ε into account and are slightly better than the ones*

in Eqs. (26),(28). However, the error criteria they consider when defining the capacities are of the average kind, as opposed to the worst case error criteria that we employ.

Proof. We start by proving the achievability bounds in Eqs. (26)-(29).

Achievability: Quantum communication (26)

Note that the action of a channel Φ on its peripheral space $\chi(\Phi)$ is reversible [Wol12, Theorem 6.16], i.e., there exists a channel $\mathcal{R} : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_A)$ such that $\mathcal{R} \circ \Phi = \mathcal{P}$ (which implies that $\mathcal{R}^n \circ \Phi^n = \mathcal{P}$), where \mathcal{P} is the projection onto the peripheral space (Eq. (22)). Thus, in the language of [KLPL06], all the $\mathcal{H}_{k,1}$ sectors in the decomposition in Eq. (24) are correctable for Φ^n for all $n \in \mathbb{N}$. Corresponding subspaces $\mathcal{C}_k \subseteq \mathcal{H}_A$ with $\dim \mathcal{C}_k = \dim \mathcal{H}_{k,1} = d_k$ can be constructed using [KLPL06, Theorem 3.7] that satisfy the so-called Knill-Laflamme error-correction conditions for Φ^n for all $n \in \mathbb{N}$ [KL97], i.e. for all $n \in \mathbb{N}$ and k , \exists channels $\mathcal{R}_{n,k} : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_A)$ such that

$$\forall \rho \in \mathcal{D}(\mathcal{C}_k) : \quad (\mathcal{R}_{n,k} \circ \Phi^n)(V_k \rho V_k^\dagger) = V_k \rho V_k^\dagger, \quad (34)$$

where $V_k : \mathcal{C}_k \hookrightarrow \mathcal{H}_A$ is the canonical embedding of \mathcal{C}_k into \mathcal{H}_A . Thus, by choosing the encoding $\mathcal{E}_k : \mathcal{L}(\mathcal{C}_k) \rightarrow \mathcal{L}(\mathcal{H}_A)$ and decoding $\mathcal{D}_{n,k} : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{C}_k)$ as follows:

$$\mathcal{E}_k(\cdot) = V_k(\cdot)V_k^\dagger, \quad \text{and} \quad \mathcal{D}_{n,k}(\cdot) = V_k^\dagger \mathcal{R}_{n,k}(\cdot)V_k + \text{Tr}[(\mathbb{1} - V_k V_k^\dagger) \mathcal{R}_{n,k}(\cdot)] \sigma_k, \quad (35)$$

where $\sigma_k \in \mathcal{D}(\mathcal{C}_k)$ is some state, we see that $\mathcal{D}_{n,k} \circ \Phi^n \circ \mathcal{E}_k = \text{id}_{\mathcal{C}_k}$, so that $(\mathcal{E}_k, \mathcal{D}_{n,k})$ forms a (d_k, ε) quantum communication protocol for Φ^n with $\varepsilon = 0$. Hence,

$$\forall n \in \mathbb{N}, \varepsilon \in [0, 1) : \quad \log \max_k d_k \leq Q_0(\Phi^n) \leq Q_\varepsilon(\Phi^n). \quad (36)$$

Achievability: Private classical communication (27)

For private classical communication, note that $Q_0(\Phi) \leq C_0^p(\Phi)$ holds for any channel Φ (see Lemma A.1), so that

$$\forall n \in \mathbb{N}, \varepsilon \in [0, 1) : \quad \log \max_k d_k \leq Q_0(\Phi^n) \leq C_0^p(\Phi^n) \leq C_\varepsilon^p(\Phi^n). \quad (37)$$

Achievability: Classical communication (28)

For classical communication, we can send $\sum_{k=1}^K d_k$ messages perfectly (i.e. with $\varepsilon = 0$ error) through Φ^n for all n by using the encoding states $\{|i_k\rangle\langle i_k| \otimes \delta_k\}$ for $k = 1, 2, \dots, K$ and $i_k = 1, 2, \dots, d_k$, where $|i_k\rangle\langle i_k|$ are the diagonal matrix units in $\mathcal{L}(\mathcal{H}_{k,1})$ and δ_k are given in Eq. (24). Note that for each k , the state $|i_k\rangle\langle i_k| \otimes \delta_k$ is supported only on $\mathcal{H}_{k,1} \otimes \mathcal{H}_{k,2}$. From the action of Φ on its peripheral space (see Eq. (25)), it is clear that the outputs of these states under Φ^n are mutually orthogonal for all n and hence, are perfectly distinguishable. Hence,

$$\forall n \in \mathbb{N}, \varepsilon \in [0, 1) : \quad \log \left(\sum_{k=1}^K d_k \right) \leq C_0(\Phi^n) \leq C_\varepsilon(\Phi^n). \quad (38)$$

Achievability: Entanglement-assisted classical communication (29)

With entanglement assistance, we can perfectly transmit $\sum_{k=1}^K d_k^2$ classical messages through Φ^n for all n . To see this, we start with an entangled state

$$\psi_{A'A} = \frac{1}{K} \oplus_{k=1}^K (\psi_k^+ \otimes \delta_k) \in \mathcal{D}(\mathcal{H}_{A'} \otimes \mathcal{H}_A) = \mathcal{D}(\oplus_k (\mathcal{H}_{A'} \otimes \mathcal{H}_{k,1} \otimes \mathcal{H}_{k,2})), \quad (39)$$

where $\psi_k^+ \in \mathcal{D}(\mathcal{H}_{A'} \otimes \mathcal{H}_{k,1})$ are maximally entangled states of Schmidt rank d_k , where $d_k = \dim \mathcal{H}_{k,1}$, and δ_k are the positive definite states given in Eq. (24). For each k , we apply an orthogonal set of unitary operators in $\mathcal{L}(\mathcal{H}_{k,1})$ locally on $\mathcal{H}_{k,1}$ to encode d_k^2 many classical messages in

orthogonal states¹, thus encoding $\sum_k d_k^2$ messages in total. The permutation+unitary action of Φ on its peripheral space (Eq. (25)) ensures that these states remain orthogonal (and hence perfectly distinguishable) after the action of $\Phi_{A \rightarrow A}^n$ for all n . Thus,

$$\forall n \in \mathbb{N}, \varepsilon \in [0, 1) : \quad \log \left(\sum_{k=1}^K d_k^2 \right) \leq C_0^{\text{ea}}(\Phi^n) \leq C_\varepsilon^{\text{ea}}(\Phi^n). \quad (40)$$

Next, we prove the converse bounds in Eqs. (30)-(33).

The proofs of these bounds for the quantum, classical, and entanglement-assisted classical capacities start similarly and so we consider them together below. Let us fix $\varepsilon \in [0, 1)$. Note that $\|\Phi^n - \Phi_\infty^n\|_\diamond \rightarrow 0$ as $n \rightarrow \infty$ and the convergence behaves like $\|\Phi^n - \Phi_\infty^n\|_\diamond \leq \kappa\mu^n$, so that for n large enough such that $\varepsilon + \kappa\mu^n < 1$, we can use Lemmas A.4 and A.7, and the fact that $\Phi_\infty^n = \Phi_\infty^n \circ \mathcal{P} = \mathcal{P} \circ \Phi_\infty^n$ for all n to write

$$Q_\varepsilon(\Phi^n) \leq Q_{\varepsilon+\kappa\mu^n}(\Phi_\infty^n) \leq Q_{\varepsilon+\kappa\mu^n}(\mathcal{P}), \quad (41)$$

$$C_\varepsilon(\Phi^n) \leq C_{\varepsilon+\kappa\mu^n}(\Phi_\infty^n) \leq C_{\varepsilon+\kappa\mu^n}(\mathcal{P}), \quad (42)$$

$$C_\varepsilon^{\text{ea}}(\Phi^n) \leq C_{\varepsilon+\kappa\mu^n}^{\text{ea}}(\Phi_\infty^n) \leq C_{\varepsilon+\kappa\mu^n}^{\text{ea}}(\mathcal{P}). \quad (43)$$

Recall that $\mathcal{P} : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_A)$ is the channel that projects onto the peripheral space (Eq. (24))

$$\chi(\Phi) = 0 \oplus \bigoplus_{k=1}^K (\mathcal{L}(\mathcal{H}_{k,1}) \otimes \delta_k), \quad (44)$$

where the direct sum is with respect to the decomposition $\mathcal{H}_A = \mathcal{H}_0 \oplus \bigoplus_{k=1}^K \mathcal{H}_{k,1} \otimes \mathcal{H}_{k,2}$. For our purposes, we can assume that \mathcal{H}_0 is the zero subspace, so that the action of \mathcal{P} becomes

$$\forall X \in \mathcal{L}(\mathcal{H}_A) : \quad \mathcal{P}(X) = \bigoplus_{k=1}^K \text{Tr}_2(P_k X P_k) \otimes \delta_k, \quad (45)$$

where $P_k \in \mathcal{L}(\mathcal{H}_A)$ is the orthogonal projection that projects onto the block $\mathcal{H}_{k,1} \otimes \mathcal{H}_{k,2}$ and Tr_2 denotes the partial trace over $\mathcal{H}_{k,2}$. We refer the readers to Appendix B for justification of this assumption.

Converse: Quantum communication (30)

For the quantum capacity, Lemma A.2 shows that

$$Q_{\varepsilon+\kappa\mu^n}(\mathcal{P}) \leq \sup_{\psi_{RA}} \inf_{\sigma_A} D_{\max}(\mathcal{P}_{A \rightarrow A}(\psi_{RA}) \| \mathbb{1}_R \otimes \sigma_A) + \log \left(\frac{1}{1 - \varepsilon - \kappa\mu^n} \right). \quad (46)$$

We bound the first term above as follows. For a pure state ψ_{RA} , we use Eq. (45) to write

$$\mathcal{P}_{A \rightarrow A}(\psi_{RA}) = \bigoplus_k \lambda_k \frac{1}{\lambda_k} \text{Tr}_2[(\mathbb{1}_R \otimes P_k) \psi (\mathbb{1}_R \otimes P_k)] \otimes \delta_k = \bigoplus_k \lambda_k \theta_k \otimes \delta_k, \quad (47)$$

¹This is exactly the encoding scheme employed in the superdense coding protocol [BW92, Wer01].

where $\lambda_k = \text{Tr}[(\mathbb{1}_R \otimes P_k)\psi(\mathbb{1}_R \otimes P_k)]$ and each θ_k is a state in $\mathcal{D}(\mathcal{H}_R \otimes \mathcal{H}_{k,1})$. Thus, by choosing $\sigma_A = \bigoplus_k \lambda_k \sigma_k \otimes \delta_k$, where σ_k are arbitrary states in $\mathcal{D}(\mathcal{H}_{k,1})$, we get

$$\begin{aligned} \inf_{\sigma} D_{\max}(\mathcal{P}_{A \rightarrow A}(\psi_{RA}) \parallel \mathbb{1}_R \otimes \sigma_A) &\leq \inf_{\{\sigma_k\}_k} D_{\max} \left(\bigoplus_k \lambda_k \theta_k \otimes \delta_k \parallel \bigoplus_k \lambda_k \mathbb{1}_R \otimes \sigma_k \otimes \delta_k \right) \\ &= \inf_{\{\sigma_k\}_k} \max_k D_{\max}(\theta_k \parallel \mathbb{1}_R \otimes \sigma_k) \\ &= \max_k \inf_{\sigma_k} D_{\max}(\theta_k \parallel \mathbb{1}_R \otimes \sigma_k) \\ &\leq \log \max_k d_k, \end{aligned} \quad (48)$$

where the first equality follows from quasi-convexity of D_{\max} (Eq. (4)), the second equality follows from Lemma A.10, and the last inequality follows from the fact that for any state ρ_{AB} ,

$$\inf_{\sigma \in \mathcal{D}(\mathcal{H}_B)} D_{\max}(\rho_{AB} \parallel \mathbb{1}_A \otimes \sigma_B) \leq D_{\max}(\rho_{AB} \parallel \mathbb{1}_A \otimes \mathbb{1}_B/d_B) \leq \log d_B. \quad (49)$$

Converse: Classical communication (32)

For the classical capacity, Lemma A.2 shows that

$$C_{\varepsilon+\kappa\mu^n}(\mathcal{P}) \leq \sup_{\rho_{MA}} \inf_{\sigma_A} D_{\max}(\mathcal{P}_{A \rightarrow A}(\rho_{MA}) \parallel \rho_M \otimes \sigma_A) + \log \left(\frac{1}{1 - \varepsilon - \kappa\mu^n} \right). \quad (50)$$

For any classical-quantum (c-q) state $\rho_{MA} = \sum_m p(m) |m\rangle\langle m| \otimes \rho_A^m$, we can write

$$\inf_{\sigma} D_{\max}(\mathcal{P}_{A \rightarrow A}(\rho_{MA}) \parallel \rho_M \otimes \sigma_A) = \inf_{\sigma} \max_m D_{\max}(\mathcal{P}_{A \rightarrow A}(\rho_A^m) \parallel \sigma_A) \leq \log \left(\sum_k d_k \right), \quad (51)$$

where the inequality follows by choosing $\sigma_A = (\bigoplus_k \mathbb{1}_k \otimes \delta_k) / \sum_k d_k$ and noting that for any state ρ , its projection $\mathcal{P}(\rho)$ onto the peripheral space is dominated by $\bigoplus_k (\mathbb{1}_k \otimes \delta_k)$ (see Eq. (45)).

Converse: Entanglement-assisted classical communication (33)

For the entanglement-assisted classical capacity, we again use Lemma A.2 to write

$$C_{\varepsilon+\kappa\mu^n}^{\text{ea}}(\mathcal{P}) \leq \sup_{\psi_{RA}} \inf_{\sigma_A} D_{\max}(\mathcal{P}_{A \rightarrow A}(\psi_{RA}) \parallel \psi_R \otimes \sigma_A) + \log \left(\frac{1}{1 - \varepsilon - \kappa\mu^n} \right), \quad (52)$$

where $d = d_A = d_R$. We note that the supremum in the above sum is achieved by the maximally entangled state $\psi_{RA}^+ = 1/d \sum_{i,j} |i\rangle\langle j| \otimes |i\rangle\langle j| =: \Gamma_{RA}/d$, where Γ_{RA} is the unnormalized maximally entangled state (see [FWTB20, Remark 2]). Now, by using Eq. (45), we write

$$\mathcal{P}_{A \rightarrow A}(\psi_{RA}^+) = \frac{1}{d} \bigoplus_k \text{Tr}_2 [(\mathbb{1}_R \otimes P_k) \Gamma_{RA} (\mathbb{1}_R \otimes P_k)] \otimes \delta_k = \frac{1}{d} \bigoplus_k \theta_k \otimes \delta_k, \quad (53)$$

where $\theta_k = \text{Tr}_2 [(\mathbb{1}_R \otimes P_k) \Gamma_{RA} (\mathbb{1}_R \otimes P_k)]$ is a positive operator in $\mathcal{L}(\mathcal{H}_R \otimes \mathcal{H}_{k,1})$ with $\text{Tr} \theta_k = d_k$. Let us choose $\sigma_A = \bigoplus_k \lambda_k (\mathbb{1}_k/d_k \otimes \delta_k)$, where $\{\lambda_k = d_k^2 / \sum_{k'} d_{k'}^2\}_k$ is a probability distribution. Then,

$$\begin{aligned} \inf_{\sigma} D_{\max}(\mathcal{P}_{A \rightarrow A}(\psi_{RA}^+) \parallel \psi_R^+ \otimes \sigma_A) &\leq D_{\max} \left(\frac{1}{d} \bigoplus_k \theta_k \otimes \delta_k \parallel \frac{1}{d} \bigoplus_k \lambda_k \mathbb{1}_R \otimes \frac{\mathbb{1}_k}{d_k} \otimes \delta_k \right) \\ &= \max_k D_{\max} \left(\theta_k \parallel \lambda_k \mathbb{1}_R \otimes \frac{\mathbb{1}_k}{d_k} \right) \\ &= \log \left(\frac{d_k}{\lambda_k} \|\theta_k\|_{\infty} \right) \leq \log(d_k^2/\lambda_k) = \log \left(\sum_k d_k^2 \right), \end{aligned} \quad (54)$$

which proves the desired result. Above, the first equality follows from quasi-convexity of D_{\max} (Eq. (4)) and the second equality follows from Eq. (3).

Converse: Private classical communication (31)

The proof of the converse bound for private classical capacity requires a slightly different line of argumentation. We again fix $\varepsilon \in [0, 1)$ and note that $\|\Phi^n - \Phi_\infty^n\|_\diamond \rightarrow 0$ as $n \rightarrow \infty$, where the convergence behaves like $\|\Phi^n - \Phi_\infty^n\|_\diamond \leq \kappa\mu^n$, so that for n large enough such that $\varepsilon + \kappa\mu^n < 1$, we can use Lemmas A.3, A.6 and A.8, and the fact that $\Phi_\infty^n = \Phi_\infty^n \circ \mathcal{P} = \mathcal{P} \circ \Phi_\infty^n$ for all n to write

$$\begin{aligned} C_\varepsilon^p(\Phi^n) &\leq E_H^\varepsilon(\Phi^n) \leq E_H^{\varepsilon+\kappa\mu^n}(\Phi_\infty^n) \\ &\leq E_H^{\varepsilon+\kappa\mu^n}(\mathcal{P}) \\ &\leq \sup_{\psi_{RA}} \inf_{\sigma_{RA} \in \text{SEP}(R:A)} D_{\max}(\mathcal{P}_{A \rightarrow A}(\psi_{RA}) \|\sigma_{RA}) + \log\left(\frac{1}{1 - \varepsilon - \kappa\mu^n}\right). \end{aligned} \quad (55)$$

We bound the first term above as follows. For a pure state ψ_{RA} , we use Eq. (45) to write

$$\mathcal{P}_{A \rightarrow A}(\psi_{RA}) = \bigoplus_k \lambda_k \frac{1}{\lambda_k} \text{Tr}_2[(\mathbb{1}_R \otimes P_k)\psi(\mathbb{1}_R \otimes P_k)] \otimes \delta_k = \bigoplus_k \lambda_k \theta_k \otimes \delta_k, \quad (56)$$

where $\lambda_k = \text{Tr}[(\mathbb{1}_R \otimes P_k)\psi(\mathbb{1}_R \otimes P_k)]$ and each θ_k is a state in $\mathcal{D}(\mathcal{H}_R \otimes \mathcal{H}_{k,1})$. Thus, by choosing $\sigma_{RA} = \bigoplus_k \lambda_k \sigma_k \otimes \delta_k$, where σ_k are arbitrary separable states in $\mathcal{D}(\mathcal{H}_R \otimes \mathcal{H}_{k,1})$, we get

$$\begin{aligned} \inf_{\sigma \in \text{SEP}(R:A)} D_{\max}(\mathcal{P}_{A \rightarrow A}(\psi_{RA}) \|\sigma_{RA}) &\leq \inf_{\{\sigma_k\}_k} D_{\max}\left(\bigoplus_k \lambda_k \theta_k \otimes \delta_k \left\| \bigoplus_k \lambda_k \sigma_k \otimes \delta_k\right.\right) \\ &= \inf_{\{\sigma_k\}_k} \max_k D_{\max}(\theta_k \|\sigma_k) \\ &= \max_k \inf_{\sigma_k} D_{\max}(\theta_k \|\sigma_k) \\ &\leq \log\left(\max_k d_k\right), \end{aligned} \quad (57)$$

where the first equality follows from Eq. (4), the second equality follows from Lemma A.10, and the last inequality follows from the fact that for any state ρ_{AB} (see Lemma A.9),

$$\inf_{\sigma \in \text{SEP}(A:B)} D_{\max}(\rho_{AB} \|\sigma_{AB}) \leq \log \min\{d_A, d_B\}. \quad (58)$$

□

Corollary 3.3. *For a channel $\Phi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_A)$ and $\varepsilon \in [0, 1)$, the following holds true:*

$$\log\left(\max_k d_k\right) \leq \lim_{n \rightarrow \infty} Q_\varepsilon(\Phi^n) \leq \log\left(\max_k d_k\right) + \log\left(\frac{1}{1 - \varepsilon}\right) \quad (59)$$

$$\log\left(\max_k d_k\right) \leq \lim_{n \rightarrow \infty} C_\varepsilon^p(\Phi^n) \leq \log\left(\max_k d_k\right) + \log\left(\frac{1}{1 - \varepsilon}\right) \quad (60)$$

$$\log\left(\sum_k d_k\right) \leq \lim_{n \rightarrow \infty} C_\varepsilon(\Phi^n) \leq \log\left(\sum_k d_k\right) + \log\left(\frac{1}{1 - \varepsilon}\right) \quad (61)$$

$$\log\left(\sum_k d_k^2\right) \leq \lim_{n \rightarrow \infty} C_\varepsilon^{\text{ea}}(\Phi^n) \leq \log\left(\sum_k d_k^2\right) + \log\left(\frac{1}{1 - \varepsilon}\right). \quad (62)$$

We now take a moment to comment on related results in the literature. As mentioned in the introduction, the problem of transmitting information across sequential concatenations of channels was recently studied in [SRD24]. In particular, the $\varepsilon = 0$ case of Corollary 3.3 for the quantum

and classical capacities (Eqs. (59), (61)) was proved in [SRD24] and was subsequently generalized for arbitrary error in [FRT24]. The $\varepsilon = 0$ case of Eq. (61) is also proved in [GFY16, Section V].

APPENDIX A. TECHNICAL RESULTS

Lemma A.1. *For a quantum channel $\Phi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_B)$, the zero-error one-shot quantum and private capacities satisfy the relation $Q_0(\Phi) \leq C_0^p(\Phi)$.*

Proof. Consider a $(\mathcal{M}, 0)$ quantum communication protocol $(\mathcal{E}_{A' \rightarrow A}, \mathcal{D}_{B \rightarrow B'})$ for Φ with $\mathcal{M} = d_{A'} = d_{B'} = d_R$, which we can use to transmit one-half of a maximally state

$$\psi_{RA'}^+ = \frac{1}{\mathcal{M}} \sum_{1 \leq m, m' \leq \mathcal{M}} |m\rangle\langle m'|_R \otimes |m\rangle\langle m'|_{A'} \quad (63)$$

of Schmidt rank \mathcal{M} through Φ perfectly, i.e.

$$\psi_{RB'}^+ = \mathcal{D}_{B \rightarrow B'} \circ \Phi_{A \rightarrow B} \circ \mathcal{E}_{A' \rightarrow A}(\psi_{RA'}^+). \quad (64)$$

Let $\mathcal{V}_{A \rightarrow BE}$ be an isometric extension of $\Phi_{A \rightarrow B}$ and consider the state

$$\omega_{RB'E} = \mathcal{D}_{B \rightarrow B'} \circ \mathcal{V}_{A \rightarrow BE} \circ \mathcal{E}_{A' \rightarrow A}(\psi_{RA'}^+), \quad (65)$$

which extends the state at the output of the protocol, i.e., $\omega_{RB'E} = \mathcal{D}_{B \rightarrow B'} \circ \Phi_{A \rightarrow B} \circ \mathcal{E}_{A' \rightarrow A}(\psi_{RA'}^+)$. Since the only possible extension of $\psi_{RB'}^+$ is of the form $\psi_{RB'}^+ \otimes \sigma_E$ for some state σ_E , we get

$$\omega_{RB'E} = \psi_{RB'}^+ \otimes \sigma_E = \mathcal{D}_{B \rightarrow B'} \circ \mathcal{V}_{A \rightarrow BE} \circ \mathcal{E}_{A' \rightarrow A}(\psi_{RA'}^+). \quad (66)$$

Applying a measurement with POVMs $\{|m\rangle\langle m|_R\}_{m \in [\mathcal{M}]}$ and $\{|m\rangle\langle m|_{B'}\}_{m \in [\mathcal{M}]}$ on the R and B' systems yields

$$\bar{\psi}_{RB'}^+ \otimes \sigma_E = \bar{\mathcal{D}}_{B \rightarrow B'} \circ \mathcal{V}_{A \rightarrow BE} \circ \mathcal{E}_{A' \rightarrow A}(\bar{\psi}_{RA'}^+), \quad (67)$$

where $\bar{\psi}_{RA'}^+ = \frac{1}{\mathcal{M}} \sum_{1 \leq m \leq \mathcal{M}} |m\rangle\langle m|_R \otimes |m\rangle\langle m|_{A'}$ is a maximally classically correlated state and $\bar{\mathcal{D}}_{B \rightarrow B'}$ is a measurement channel defined as

$$\begin{aligned} \bar{\mathcal{D}}_{B \rightarrow B'}(X_B) &= \sum_m \text{Tr}(|m\rangle\langle m|_{B'} \mathcal{D}_{B \rightarrow B'}(X_B)) |m\rangle\langle m|_{B'} \\ &= \sum_m \text{Tr}(\mathcal{D}_{B' \rightarrow B}^*(|m\rangle\langle m|_{B'}) X_B) |m\rangle\langle m|_{B'}. \end{aligned} \quad (68)$$

Note that $\{\mathcal{D}_{B' \rightarrow B}^*(|m\rangle\langle m|_{B'})\}_{m=1}^{\mathcal{M}}$ forms a POVM, since $\mathcal{D}_{B' \rightarrow B}^*$ is unital. Expanding the LHS and RHS of the Eq. (67) by using the formula for $\bar{\psi}^+$ and matching terms shows that for each $m \in [\mathcal{M}]$,

$$|m\rangle\langle m|_{B'} \otimes \sigma_E = \bar{\mathcal{D}}_{B \rightarrow B'} \circ \mathcal{V}_{A \rightarrow BE}(\rho_A^m), \quad (69)$$

where the states ρ^m are defined as $\rho_A^m = \mathcal{E}_{A' \rightarrow A}(|m\rangle\langle m|_{A'})$. Thus, the encoding states ρ_A^m for $m \in [\mathcal{M}]$ and the decoding POVM $\{\mathcal{D}_{B' \rightarrow B}^*(|m\rangle\langle m|_{B'})\}_{m=1}^{\mathcal{M}}$ forms a $(\mathcal{M}, 0)$ private classical communication protocol for Φ . Since the quantum communication protocol that we started with was arbitrary, we obtain the desired result. \square

Lemma A.2. *For any channel $\Phi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_B)$ and $\varepsilon \in [0, 1)$, the following bounds hold:*

$$Q_\varepsilon(\Phi) \leq \sup_{\psi_{RA}} \inf_{\sigma_B} D_{\max}(\Phi_{A \rightarrow B}(\psi_{RA}) || \mathbb{1}_R \otimes \sigma_B) + \log\left(\frac{1}{1-\varepsilon}\right), \quad (70)$$

$$C_\varepsilon(\Phi) \leq \sup_{\rho_{MA}} \inf_{\sigma_B} D_{\max}(\Phi_{A \rightarrow B}(\rho_{MA}) || \rho_M \otimes \sigma_B) + \log\left(\frac{1}{1-\varepsilon}\right), \quad (71)$$

$$C_\varepsilon^{\text{ea}}(\Phi) \leq \sup_{\psi_{RA}} \inf_{\sigma_B} D_{\max}(\Phi_{A \rightarrow B}(\psi_{RA}) || \psi_R \otimes \sigma_B) + \log\left(\frac{1}{1-\varepsilon}\right), \quad (72)$$

where the supremum is either over pure states $\psi_{RA} \in \mathcal{D}(\mathcal{H}_R \otimes \mathcal{H}_A)$ with $d_R = d_A$ or classical-quantum states $\rho_{MA} = \sum_m p(m) |m\rangle\langle m|_M \otimes \rho_A^m \in \mathcal{D}(\mathcal{H}_M \otimes \mathcal{H}_A)$, and the infimum is over arbitrary states $\sigma_B \in \mathcal{D}(\mathcal{H}_B)$.

Proof. For a unified account of these bounds, we refer the readers to [KW24, Chapters 11-14]. In particular, we make use of [KW24, Theorem 11.6, Theorem 12.4, Corollary 14.4]. See also the Bibliographic notes for references to original papers where these bounds were first established. \square

Lemma A.3. *For any channel $\Phi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_B)$ and $\varepsilon \in [0, 1)$, the following bound holds:*

$$C_\varepsilon^p(\Phi) \leq E_H^\varepsilon(\Phi) \leq \sup_{\psi_{RA}} \inf_{\sigma_{RB} \in \text{SEP}(R:B)} D_{\max}(\Phi_{A \rightarrow B}(\psi_{RA}) \| \sigma_{RB}) + \log\left(\frac{1}{1-\varepsilon}\right), \quad (73)$$

where the supremum is over all pure states ψ_{RA} with $d_R = d_A$.

Proof. The first inequality was proved in [WTB17, Theorem 11]. The second inequality follows from the inequality

$$D_H^\varepsilon(\rho \| \sigma) \leq D_{\max}(\rho \| \sigma) + \log\left(\frac{1}{1-\varepsilon}\right), \quad (74)$$

which holds for any two states $\rho, \sigma \in \mathcal{D}(\mathcal{H}_A)$ and was established in [CMW16, Lemma 5]. \square

Lemma A.4. *Let $\Phi, \Psi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_B)$ be quantum channels such that $\|\Phi - \Psi\|_\diamond \leq \delta$. Then, for $\varepsilon \in [0, 1)$ such that $\varepsilon + \delta < 1$:*

$$Q_\varepsilon(\Phi) \leq Q_{\varepsilon+\delta}(\Psi) \quad (75)$$

$$C_\varepsilon(\Phi) \leq C_{\varepsilon+\delta}(\Psi) \quad (76)$$

$$C_\varepsilon^{\text{ea}}(\Phi) \leq C_{\varepsilon+\delta}^{\text{ea}}(\Psi) \quad (77)$$

Proof. Consider a (M, ε) classical communication protocol $\{\rho_A^m, \Lambda_B^m\}_{m=1}^M$ for $\Phi_{A \rightarrow B}$ as in Section 2.1. This means that for each message m ,

$$\text{Tr}[\Lambda_B^m(\Phi_{A \rightarrow B}(\rho_A^m))] \geq 1 - \varepsilon. \quad (78)$$

For each m , it is then easy to see that

$$\begin{aligned} \text{Tr}[\Lambda_B^m(\Psi_{A \rightarrow B}(\rho_A^m))] &= \text{Tr}[\Lambda_B^m(\Phi_{A \rightarrow B}(\rho_A^m))] - \text{Tr}[\Lambda_B^m(\Phi - \Psi)_{A \rightarrow B}(\rho_A^m)] \\ &\geq 1 - (\varepsilon + \delta), \end{aligned} \quad (79)$$

where the last inequality follows from the fact that

$$\begin{aligned} \text{Tr}[\Lambda_B^m(\Phi - \Psi)_{A \rightarrow B}(\rho_A^m)] &\leq \|\Lambda_B^m\|_\infty \|(\Phi - \Psi)_{A \rightarrow B}(\rho_A^m)\|_1 \\ &\leq \|\Phi - \Psi\|_\diamond \leq \delta. \end{aligned} \quad (80)$$

Hence, $\{\rho_A^m, \Lambda_B^m\}_{m=1}^M$ works as a $(M, \varepsilon + \delta)$ classical communication protocol for $\Psi_{A \rightarrow B}$.

Consider a (d, ε) quantum communication protocol $(\mathcal{E}_{A' \rightarrow A}, \mathcal{D}_{B \rightarrow B'})$ for $\Phi_{A \rightarrow B}$ such that

$$\forall \psi_{RB'} : \text{Tr}[\psi_{RB'}(\mathcal{D}_{B \rightarrow B'} \circ \Phi_{A \rightarrow B} \circ \mathcal{E}_{A' \rightarrow A}(\psi_{RA'}))] \geq 1 - \varepsilon, \quad (81)$$

where $d = d_{A'} = d_{B'} = d_R$. For any $\psi_{RA'}$, it is then easy to see that

$$\begin{aligned} &\text{Tr}[\psi_{RB'}(\mathcal{D}_{B \rightarrow B'} \circ \Psi_{A \rightarrow B} \circ \mathcal{E}_{A' \rightarrow A}(\psi_{RA'}))] \\ &= \text{Tr}[\psi_{RB'}(\mathcal{D}_{B \rightarrow B'} \circ \Phi_{A \rightarrow B} \circ \mathcal{E}_{A' \rightarrow A}(\psi_{RA'}))] - \text{Tr}[\psi_{RB'}(\mathcal{D}_{B \rightarrow B'} \circ (\Phi - \Psi)_{A \rightarrow B} \circ \mathcal{E}_{A' \rightarrow A}(\psi_{RA'}))] \\ &\geq 1 - (\varepsilon + \delta), \end{aligned} \quad (82)$$

where the last inequality follows from the fact that

$$\begin{aligned} \text{Tr}[\psi_{RB'}(\mathcal{D}_{B \rightarrow B'} \circ (\Phi - \Psi)_{A \rightarrow B} \circ \mathcal{E}_{A' \rightarrow A}(\psi_{RA'}))] &\leq \|\mathcal{D}_{B \rightarrow B'} \circ (\Phi - \Psi)_{A \rightarrow B} \circ \mathcal{E}_{A' \rightarrow A}\|_\diamond \\ &\leq \|\Phi - \Psi\|_\diamond \leq \delta, \end{aligned} \quad (83)$$

where we have used sub-multiplicativity of the diamond norm [Wat18, Proposition 3.48] and the fact that $\|\Phi\|_\diamond = 1$ for any channel Φ [Wat18, Proposition 3.44]. Thus, $(\mathcal{E}_{A' \rightarrow A}, \mathcal{D}_{B \rightarrow B'})$ works as a $(d, \varepsilon + \delta)$ quantum communication protocol for $\Psi_{A \rightarrow B}$. The proof for the entanglement-assisted classical capacity works similarly. \square

Lemma A.5. *Let ρ_{AB}, ω_{AB} be states such that $\|\rho - \omega\|_1 \leq \delta$. Then, $E_H^\varepsilon(A : B)_\rho \leq E_H^{\varepsilon+\delta}(A : B)_\omega$.*

Proof. Fix a separable state σ_{AB} . Then, for every $\Lambda \in \mathcal{L}(\mathcal{H}_A \otimes \mathcal{H}_B)$ satisfying $0 \leq \Lambda \leq \mathbb{1}$ and $\text{Tr} \Lambda \rho \geq 1 - \varepsilon$, we have $\text{Tr} \Lambda \omega = \text{Tr} \Lambda \rho - \text{Tr} \Lambda (\rho - \omega) \geq 1 - (\varepsilon + \delta)$. Hence, $\beta_H^\varepsilon(\rho \| \sigma) \geq \beta_H^{\varepsilon+\delta}(\omega \| \sigma)$ and $D_H^\varepsilon(\rho \| \sigma) \leq D_H^{\varepsilon+\delta}(\omega \| \sigma)$. The claim follows by taking an infimum over all separable states σ_{AB} . \square

Lemma A.6. *Let $\Phi, \Psi : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_B)$ be quantum channels such that $\|\Phi - \Psi\|_\diamond \leq \delta$. Then,*

$$E_H^\varepsilon(\Phi) \leq E_H^{\varepsilon+\delta}(\Psi) \quad (84)$$

Proof. For any pure state ψ_{RA} , $\|\Phi_{A \rightarrow B}(\psi_{RA}) - \Psi_{A \rightarrow B}(\psi_{RA})\|_1 \leq \delta$ because $\|\Phi - \Psi\|_\diamond \leq \delta$. Thus, the claim follows from the definition (Eq. (8)) and Lemma A.5. \square

Lemma A.7. *Let $\Psi_{A \rightarrow B}, \Phi_{B \rightarrow C}$ be quantum channels. Then, for any $\varepsilon \in [0, 1)$:*

$$Q_\varepsilon(\Phi \circ \Psi) \leq \min\{Q_\varepsilon(\Phi), Q_\varepsilon(\Psi)\}, \quad (85)$$

$$C_\varepsilon(\Phi \circ \Psi) \leq \min\{C_\varepsilon(\Phi), C_\varepsilon(\Psi)\}, \quad (86)$$

$$C_\varepsilon^{\text{ea}}(\Phi \circ \Psi) \leq \min\{C_\varepsilon^{\text{ea}}(\Phi), C_\varepsilon^{\text{ea}}(\Psi)\}. \quad (87)$$

Proof. Consider a (d, ε) quantum communication protocol $(\mathcal{E}_{A' \rightarrow A}, \mathcal{D}_{C \rightarrow C'})$ for $\Phi \circ \Psi$, with $d = d_{A'} = d_{C'}$, such that for any pure state $\psi_{RA'} \in \mathcal{D}(\mathcal{H}_R \otimes \mathcal{H}_{A'})$

$$\langle \psi_{RC'} | \mathcal{D}_{C \rightarrow C'} \circ (\Phi \circ \Psi)_{A \rightarrow C} \circ \mathcal{E}_{A' \rightarrow A}(\psi_{RA'}) | \psi_{RC'} \rangle \geq 1 - \varepsilon. \quad (88)$$

Now, by absorbing either Ψ into the encoding channel $\mathcal{E}_{A' \rightarrow A}$ or Φ into the decoding channel $\mathcal{D}_{C \rightarrow C'}$, we see that the same (d, ε) protocol works for Φ and Ψ , which proves the desired result. We leave similar proofs for the other capacities to the reader. \square

Lemma A.8. *Let $\Psi_{A \rightarrow B}, \Phi_{B \rightarrow C}$ be quantum channels. Then, for any $\varepsilon \in [0, 1)$:*

$$E_H^\varepsilon(\Phi \circ \Psi) \leq \min\{E_H^\varepsilon(\Phi), E_H^\varepsilon(\Psi)\}. \quad (89)$$

Proof. The inequality $E_H^\varepsilon(\Phi \circ \Psi) \leq E_H^\varepsilon(\Psi)$ is an easy consequence of the fact that the ε -hypothesis testing relative entropy D_H^ε satisfies the data processing inequality. For the inequality $E_H^\varepsilon(\Phi \circ \Psi) \leq E_H^\varepsilon(\Phi)$, note that for any state ρ_{RA} and $\omega_{RB} = \Psi_{A \rightarrow B}(\rho_{RA})$,

$$\inf_{\sigma \in \text{SEP}(R:C)} D_H^\varepsilon(\Phi_{B \rightarrow C}(\Psi_{A \rightarrow B}(\rho_{RA})) \| \sigma_{RC}) = \inf_{\sigma \in \text{SEP}(R:C)} D_H^\varepsilon(\Phi_{B \rightarrow C}(\omega_{RB}) \| \sigma_{RC}) \leq E_H^\varepsilon(\Phi). \quad (90)$$

\square

Lemma A.9. *For any state $\rho_{AB} \in \mathcal{D}(\mathcal{H}_A \otimes \mathcal{H}_B)$,*

$$\inf_{\sigma \in \text{SEP}(A:B)} D_{\max}(\rho_{AB} \| \sigma_{AB}) \leq \log \min\{d_A, d_B\}. \quad (91)$$

Proof. Consider the spectral decomposition $\rho_{AB} = \sum_i p_i \psi_{AB}^i$, where ψ_{AB}^i are pure states and $\sum_i p_i = 1$, so that we can write

$$\begin{aligned} \inf_{\sigma \in \text{SEP}(A:B)} D_{\max}(\rho_{AB} \| \sigma_{AB}) &\leq \inf_{\{\sigma^i\}_i \subset \text{SEP}(A:B)} D_{\max} \left(\sum_i p_i \psi_{AB}^i \left\| \sum_i p_i \sigma_{AB}^i \right. \right) \\ &\leq \inf_{\{\sigma^i\}_i \subset \text{SEP}(A:B)} \max_i D_{\max}(\psi_{AB}^i \| \sigma_{AB}^i) \\ &= \max_i \inf_{\sigma^i \in \text{SEP}(A:B)} D_{\max}(\psi_{AB}^i \| \sigma_{AB}^i). \end{aligned} \quad (92)$$

Note that we made use of quasi-convexity of D_{\max} (Eq. (4)) to obtain the second inequality above and of Lemma A.10 to obtain the last equality. Thus, it suffices to prove the claim for pure states. For a pure state ψ_{AB} , it is known that [Dat09a]

$$\inf_{\sigma \in \text{SEP}(A:B)} D_{\max}(\psi_{AB} \| \sigma_{AB}) = 2 \log \left(\sum_{i=1}^d \lambda_i \right), \quad (93)$$

where $\lambda_i \geq 0$ are the Schmidt coefficients of ψ_{AB} satisfying $\sum_{i=1}^d \lambda_i^2 = 1$ and $d = \min\{d_A, d_B\}$. A simple application of Cauchy-Schwarz inequality then shows

$$\sum_i \lambda_i \leq \sqrt{d \sum_i \lambda_i^2} = \sqrt{d}, \quad (94)$$

Hence,

$$\inf_{\sigma \in \text{SEP}(A:B)} D_{\max}(\psi_{AB} \| \sigma_{AB}) = 2 \log \left(\sum_{i=1}^d \lambda_i \right) \leq 2 \log \sqrt{d} = \log d = \log \min\{d_A, d_B\}. \quad (95)$$

□

Lemma A.10. *Let $f_k : \mathcal{S} \rightarrow \mathbb{R}$ for $k = 1, 2, \dots, K$ be arbitrary mappings, where \mathcal{S} is an arbitrary set. Then,*

$$\inf_{\{x_k\}_k \subset \mathcal{S}} \left(\max_k f_k(x_k) \right) = \max_k \left(\inf_{x \in \mathcal{S}} f_k(x) \right). \quad (96)$$

Proof. Clearly, for any subset $\{x_k\}_k \subset \mathcal{S}$, we have

$$\max_k \left(\inf_{x \in \mathcal{S}} f_k(x) \right) \leq \max_k f_k(x_k), \quad (97)$$

so that

$$\max_k \left(\inf_{x \in \mathcal{S}} f_k(x) \right) \leq \inf_{\{x_k\}_k \subset \mathcal{S}} \left(\max_k f_k(x_k) \right). \quad (98)$$

Next we justify that the above inequality cannot be strict. Note that for any $\delta > 0$, the number $\max_k (\inf_{x \in \mathcal{S}} f_k(x)) + \delta$, by definition, cannot be a lower bound on the sets $\{f_k(x)\}_{x \in \mathcal{S}}$ for all k . In other words, for every $\delta > 0$, there exists a subset $\{x_k\}_k \subset \mathcal{S}$ such that for each k , $f_k(x_k) < \max_k (\inf_{x \in \mathcal{S}} f_k(x)) + \delta$, which means that

$$\max_k f_k(x_k) < \max_k \left(\inf_{x \in \mathcal{S}} f_k(x) \right) + \delta. \quad (99)$$

Hence, $\max_k (\inf_{x \in \mathcal{S}} f_k(x))$ must be the greatest lower bound on the set $\{\max_k f_k(x_k)\}_{\{x_k\}_k \subset \mathcal{S}}$, which is what we want to prove:

$$\max_k \left(\inf_{x \in \mathcal{S}} f_k(x) \right) = \inf_{\{x_k\}_k \subset \mathcal{S}} \left(\max_k f_k(x_k) \right). \quad (100)$$

□

APPENDIX B. JUSTIFICATION FOR THE ASSUMPTION THAT $\mathcal{H}_0 = \{0\}$

Consider the decomposition $\mathcal{H}_A = \mathcal{H}_0 \oplus \mathcal{H}_0^\perp$, where we have identified $\mathcal{H}_0^\perp = \bigoplus_{k=1}^K \mathcal{H}_{k,1} \otimes \mathcal{H}_{k,2}$. Let $V : \mathcal{H}_0^\perp \hookrightarrow \mathcal{H}_A$ be the canonical embedding. Then, since $\mathcal{P} : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_A)$ projects onto the peripheral space $\chi(\Phi) = 0 \oplus \bigoplus_{k=1}^K (\mathcal{L}(\mathcal{H}_{k,1}) \otimes \delta_k)$, it is clear that

$$\forall X \in \mathcal{L}(\mathcal{H}_A) : \quad \mathcal{P}(X) = 0 \oplus V^\dagger \mathcal{P}(X) V = 0 \oplus \mathcal{R}_V \circ \mathcal{P}(X), \quad (101)$$

where the channel $\mathcal{R}_V : \mathcal{L}(\mathcal{H}_A) \rightarrow \mathcal{L}(\mathcal{H}_0^\perp)$ is defined as $\mathcal{R}_V(Y) = V^\dagger Y V + \text{Tr}[(\mathbb{1} - VV^\dagger)Y]\sigma$ for some state $\sigma \in \mathcal{D}(\mathcal{H}_0^\perp)$. Moreover, since $\mathcal{P} = \mathcal{P}^2$, we get

$$\mathcal{P}(X) = \mathcal{P}(\mathcal{P}(X)) = \mathcal{P}(0 \oplus \mathcal{R}_V \circ \mathcal{P}(X)) = 0 \oplus \bar{\mathcal{P}} \circ \mathcal{R}_V \circ \mathcal{P}(X), \quad (102)$$

where $\bar{\mathcal{P}} : \mathcal{L}(\mathcal{H}_0^\perp) \rightarrow \mathcal{L}(\mathcal{H}_0^\perp)$ is defined as (see [LG16, Theorem 12])

$$\forall X \in \mathcal{L}(\mathcal{H}_0^\perp) : \quad \bar{\mathcal{P}}(X) = \bigoplus_{k=1}^K \text{Tr}_2(P_k X P_k) \otimes \delta_k. \quad (103)$$

Here, $P_k \in \mathcal{L}(\mathcal{H}_0^\perp)$ is the orthogonal projection that projects onto the block $\mathcal{H}_{k,1} \otimes \mathcal{H}_{k,2}$ and Tr_2 denotes the partial trace over $\mathcal{H}_{k,2}$. Therefore, Lemma A.7 show that the capacities of \mathcal{P} are upper bounded by those of $\bar{\mathcal{P}}$. Hence, we can assume that \mathcal{H}_0 is the zero subspace, because if not, we can just work with the $\bar{\mathcal{P}}$ channel instead of \mathcal{P} .

REFERENCES

- [BW92] Charles H. Bennett and Stephen J. Wiesner. Communication via one- and two-particle operators on einstein-podolsky-rosen states. *Phys. Rev. Lett.*, 69:2881–2884, Nov 1992. [7](#)
- [CMW16] Tom Cooney, Milán Mosonyi, and Mark M. Wilde. Strong converse exponents for a quantum channel discrimination problem and quantum-feedback-assisted communication. *Communications in Mathematical Physics*, 344(3):797–829, May 2016. [11](#)
- [Dat09a] Nilanjana Datta. Max-relative entropy of entanglement, alias log robustness. *Int. J. Quantum Inf.*, 07(02):475–491, March 2009. [13](#)
- [Dat09b] Nilanjana Datta. Min- and max-relative entropies and a new entanglement monotone. *IEEE Transactions on Information Theory*, 55(6):2816–2826, June 2009. [2](#)
- [FRT24] Omar Fawzi, Mizanur Rahaman, and Mostafa Taheri. Capacities of quantum markovian noise for large times. *preprint arXiv:2408.00116*, 2024. [1](#), [5](#), [10](#)
- [FWTB20] Kun Fang, Xin Wang, Marco Tomamichel, and Mario Berta. Quantum channel simulation and the channel’s smooth max-information. *IEEE Transactions on Information Theory*, 66(4):2129–2140, April 2020. [8](#)
- [GFY16] Ji Guan, Yuan Feng, and Mingsheng Ying. Decomposition of quantum markov chains and zero-error capacity. *preprint arXiv:1608.06024v1*, 2016. [1](#), [10](#)
- [KL97] Emanuel Knill and Raymond Laflamme. Theory of quantum error-correcting codes. *Phys. Rev. A*, 55:900–911, Feb 1997. [6](#)
- [KLPL06] David W. Kribs, Raymond Laflamme, David Poulin, and Maia Lesosky. Operator quantum error correction. *Quantum Inf. Comput.*, 6(4):382–399, 2006. [6](#)
- [KW24] Sumeet Khatri and Mark M. Wilde. Principles of quantum communication theory: A modern approach. *arXiv:2011.04672*, 2024. [11](#)
- [LG16] L. Lami and V. Giovannetti. Entanglement-saving channels. *Journal of Mathematical Physics*, 57(3), March 2016. [14](#)
- [SRD24] Satvik Singh, Mizanur Rahaman, and Nilanjana Datta. Zero-error communication under discrete-time markovian dynamics. *preprint arXiv:2402.18703*, 2024. [1](#), [9](#), [10](#)
- [SRW14] Oleg Szehr, David Reeb, and Michael M. Wolf. Spectral convergence bounds for classical and quantum markov processes. *Communications in Mathematical Physics*, 333(2):565–595, October 2014. [4](#)
- [Wat18] John Watrous. *The Theory of Quantum Information*. Cambridge University Press, 2018. [12](#)
- [Wer01] R F Werner. All teleportation and dense coding schemes. *Journal of Physics A: Mathematical and General*, 34(35):7081–7094, August 2001. [7](#)
- [Wol12] M. M. Wolf. Quantum channels and operations: Guided tour. (*unpublished*), 2012. [4](#), [5](#), [6](#)
- [WR12] Ligong Wang and Renato Renner. One-shot classical-quantum capacity and hypothesis testing. *Phys. Rev. Lett.*, 108:200501, May 2012. [3](#)
- [WTB17] Mark M. Wilde, Marco Tomamichel, and Mario Berta. Converse bounds for private communication over quantum channels. *IEEE Transactions on Information Theory*, 63(3):1792–1817, March 2017. [11](#)

Email address: satviksingh2@gmail.com

DEPARTMENT OF APPLIED MATHEMATICS AND THEORETICAL PHYSICS,
UNIVERSITY OF CAMBRIDGE, CAMBRIDGE, UNITED KINGDOM

Email address: n.datta@damtp.cam.ac.uk

DEPARTMENT OF APPLIED MATHEMATICS AND THEORETICAL PHYSICS,
UNIVERSITY OF CAMBRIDGE, CAMBRIDGE, UNITED KINGDOM